

# XTP 63 INVERTER PLASMA CUTTER



- CUTS ANY METAL  
- 20MM  
PRODUCTION CUT  
- 30MM  
SEVERANCE CUT

## VARIABLE OUTPUT

The variable output of the XTP 63 makes it ideal for cutting metals up to 20mm thick. Infinite power control allows the output to be tuned to minimise dross on the cut edges.

The pilot arc automatically re-ignites enabling easy cutting of mesh or perforated materials. Non HF ignition minimises the risk of interference with electronic systems.

## GENERATOR FRIENDLY

The XTP 63 is able to cope with inputs which fluctuate by +/-15% & can be used with the majority of generators. The machine is housed in a metal case with carry handle.



## KEY FEATURES

- 400V 3 phase
- Lightweight 13kg
- 60A @ 40% duty cycle
- Generator friendly
- Ideal for mesh cutting
- 20mm production cut
- 30mm severance cut
- Supplied with XT4000 plasma torch 6m & 3m earth cable
- Auto over voltage & over current protection
- Includes built in air pressure regulator & pressure gauge
- 3 Years return to base warranty + 3 years servicing plan
- Manufactured to IP23S, ISO/IEC 60974-1, ISO/IEC 60974-6 & RoHS Compliant

PARAMETER	VALUE
Output Current	10-60A
Input Voltage	400V 3P
Duty Cycle	60A @ 40%
Production Cut Capacity	20mm
Severance Cut Capacity	30mm
Starting Method	Short Circuit
Min Fuse Rating	20A
Input Current (Eff)	7.6
KVA	7
Generator Size*	10 KVA
Enclosure Protection	IP23S
Dimensions (LxWxH mm)	450 x 170 x 310
Weight (kg)	13

\*Generator requires AVC

Requires compressor that can deliver 125 Lpm @ 5 Bar, 4.5CFM @ 75 PSI

STOCK CODE	DESCRIPTION
XTP63	Inverter Plasma Cutter c/w XT4000 Torch 400V

**For full package contents see page 328**

## ACCESSORY INFORMATION:

STOCK CODE	DESCRIPTION
XTP40-6-CC10	Torch Package 4m Central Connector
CKC403	Earth Cable Clamp Kit 3m
XTI40AK	Plasma Spares Kit Plastic Box
XR935H	Light Reactive Welding Helmet



**PARWELD TV**  
See Parweld Machines in action on Parweld TV, with new machines added regularly

**WARRANTY VALID FOR UK & IRELAND ONLY**

**XT4000 TORCH**  
See pages 277 for more information.